

# SISTEMAS DE CONTROL

## Panel con micrófono de emergencia

### ME-200L

Panel de bomberos con micrófono para emisiones de emergencia destinadas a evacuar a los ocupantes del edificio en situaciones críticas. Además del micrófono dinámico de mano con tecla TALK para anuncios en directo, el panel permite activar el modo de emergencia y enviar mensajes pregrabados de aviso y evacuación, con la opción de reiniciar la unidad. Incorpora dos indicadores LED de monitorización: uno para el nivel de audio y otro para la activación del canal. Se instala en el frontal de la matriz de audio COMPACT LITE.



- Pulsador EMERGENCY, luminoso, con protector de seguridad.
- Pulsador WARNING, con indicador luminoso.
- Pulsador EVACUATION, con indicador luminoso.
- Pulsador RESET (finalización del modo emergencia).
- Indicador de habla (TALK).
- Indicador de audio del micrófono (SIGNAL)

|                       |                                                                                                                                               |
|-----------------------|-----------------------------------------------------------------------------------------------------------------------------------------------|
| Conector micrófono    | DIN 5 pins 180°, metálico, con rosca.                                                                                                         |
| Sensibilidad          | -60dB.                                                                                                                                        |
| Pulsadores            | EMERGENCY, WARNING, EVACUATION & RESET                                                                                                        |
| Indicadores luminosos | TALK & SIGNAL                                                                                                                                 |
| Alimentación          | A través de la matriz.                                                                                                                        |
| Consumo               | 250 mA                                                                                                                                        |
| Dimensiones (panel)   | 76,7 mm x 42,2 mm                                                                                                                             |
| Acabados              | Frontal color Pantone 202C                                                                                                                    |
| Micrófono             | De mano, dinámico.<br>Baja impedancia.<br>Con botón PTT.<br>300-6.000Hz, 2,5mV/Pa/1kHz, 500Ω.<br>Cable rizado, 1,5 metros (máxima extensión). |

## Fireman panel with microphone

### ME-200L

Fireman's panel with microphone for emergency broadcasts to evacuate building occupants in emergency situations. In addition to the dynamic hand-held microphone with TALK button for live announcements, the panel allows activation of the emergency mode and sends prerecorded warning and evacuation messages, with the option to reset the unit. It includes two LED monitoring indicators: one for the audio level and another for the channel activation. It is installed on the front of the COMPACT LITE audio matrix.



- Pulsador EMERGENCY luminoso, con protector de seguridad
- EMERGENCY button, illuminated, with safety guard
- WARNING button, with illuminated indicator
- EVACUATION button, with illuminated indicator
- RESET button (ends emergency mode)
- TALK indicator
- Microphone audio indicator (SIGNAL)

|                      |                                                                                                                                                    |
|----------------------|----------------------------------------------------------------------------------------------------------------------------------------------------|
| Microphone Connector | DIN 5-pin 180°, metallic, with screw lock.                                                                                                         |
| Sensitivity          | -60 dB.                                                                                                                                            |
| Push Buttons         | EMERGENCY, WARNING, EVACUATION & RESET                                                                                                             |
| Indicator Lights     | TALK & SIGNAL                                                                                                                                      |
| Power Supply         | Through the matrix.                                                                                                                                |
| Power Consumption    | 250 mA                                                                                                                                             |
| Dimensions (Panel)   | 76.7 mm × 42.2 mm                                                                                                                                  |
| Finish               | Front panel color Pantone 202C                                                                                                                     |
| Microphone           | Handheld, dynamic.<br>Low impedance.<br>With PTT button.<br>300-6,000 Hz, 2.5 mV/Pa/1 kHz, 500 Ω.<br>Coiled cable, 1.5 meters (maximum extension). |